minicompact

portable electronic organ

D.W.G. NO


FARFISA


ASPIC TERME-ANCONA - ITALY


SM-52


SCHEMATIC DIAGRAM - FOR MODEL


MINICOMPACT











FARFISA S. D. A.

Description

VALUES OF G.10 GENERATOR BOARDS

DIVIDERS

Code 74/23

Di-wine No. A4/77

		Co	C 1A	0.13	۸۵ٌ٥.	C 2B	C 3A	C 3B	C4A	C 4B	C 5 A	C 5B	СБА	C 6B
С	ĎО	7.5n	5 . 6n	6,8 n	10 n	12n	22 n	27n	39n	47n	.82n	100n	150n	170n
C**	D0#	16 n	8,2n	12n	18n	27n	33n	39n -	68 n	82n	120 n	150 n		
D	RE	14.7 n	8,2 n	10 n	15 n	22 n	33 n	39 n	68 n	82n	120n	150 n		
D#	RE#	13 n.	8.2n	10 n	15 n	22 n	33 n	39 n	68n	82n	120n	150 n		1
E	МІ	11,2 n	6,8 n	10 n	15n	22 n	27n	39n	56n	82n	120n	150n		
F	FΑ	10 n	6,8 n	10 n	15n	18 n	27n	39n	56n	68n	120n	150n		4
F#	FA#	9n	6.8n	10 n	12 n	18 n	27 n	33n	.56 n	68 n	100n	120 n	-(
G	s0L	7.8 n	5.6 n	10 n	12 n	15n	22n	33n	56n	6 <i>6</i> n	100n	`120n		
G*	SOL#	7.1 n	5,6n	3.2n	12 n	15 n	22n	33n	47n	58n	82n	100n		
. А	LA	5.9n	5.6n	32 n	10 n	15n	22n	33n	47n	68n	82n	100 n		
A*	L A #	10n	5,6 n	5,8n	*0n	12n	22n	33 n	47n	5 6n	82n	100 n		
В	SI .	8 .3 n	4,7n	5. 3 n	8,2n	12n	18 n	2 7 n	39n	47n	82n	10 Q n		

ALL CAPACITORS 10 %

Drawn by

Checked by

Dale' 29-4-66

Revis ons